

Withwave's Power Divider offer frequency range from 18 to 26.5 GHz and low insertion loss & VSWR.

This divider (PD180265-2-SF) is capable of handing C.W power up to 20 Watt (Max.)



■ Features

- 3 Way Type
- 2.92 mm Connector (Female)
- CW Power : 20 Watt (Max.)

■ Specification

Scope	Specification	PD180265-2-29SF
Electrical	Impedance	50 Ohm
	Freq. range	18 to 26.5 GHz
	Insertion Loss	1.2 dB
	Isolation	18 dB (min.)
	VSWR	1.50 : 1
	Phase Bal.	± 4 dB
	Amplitude Bal.	± 0.3 dB
	CW Power (Max.)	20 W
	Peak Power (Max.)	3 KW
Mechanical	Port Connector	2.92 mm (Female)
	Weight	45 g

■ Drawing

Unit : mm

